

GT5-U312D-FD

GT5-U312D-FD

JOUJYE unique fan delay design: It has to be used with JOUJYE Multi-link PSU. When connecting system fan to this fan delay port, all fans will keep running after computer shut down.

- > SATA dock: to install 5.25" & 2.5" HDD easily
- > CPU cooler window on case board: to install CPU cooler without removing motherboard
- > All HDD trays support 2.5" HDDs (6 internal HDD tray)
- > Ready to use super speed USB 3.0
- > Supports water cooling
- > Easy to detach HDD holder
- > Advanced cable management routes
- > Screw-less design for 5.25" devices
- > Bottom mounted PSU design

SPECIFICATIONS:

Model Name:	GT5-U312D-FD
Drive Bays:	4 x External 5.25" or 3 x 5.25" + 1 x 3.5" Drive Bays 6 x Internal HDD trays for 3,5" or 2,5" with vibration absorber
Front I/O Access	1 x USB 3.0 2 x USB 2.0 1 x E-Sata 1 x Audio 1 x Mic
Expansion Slots:	8 Slots screwless with clips
Mainboard:	ATX, Micro-ATX
Power Supply:	P/S2 ATX with all-around vibration absorber + additional fixing belt
Ventilation:	2 x 120mm (1 x included) front 1 x 120mm (included) rear 2 x 120mm or 2 x 140mm (top side) 2 x 120mm or 2 x 140mm (bottom side / 2 nd fan if 1xHDD cage is removed)
Filter:	Top and bottom side (removable)
Fan Delay Board:	1 x (to control up to 3 x system fans)
Water Cooling Support :	4 x
Colour:	Black
Chassis:	Metal / 0,8mm
Dimensions:	520mm (D) x 221mm(W) x 450mm (H)
Weight N.W:	9Kg
Complies with:	CE & FCC, RoHS

Special Features

> Fan Delay.

The fan delay kit needs to be connected to the multi-link connector on JOUJYE gaming power supply. All system fans connected to the fan delay socket will keep running a couple minutes, after shutting down the compute. This function will cool down all computer parts and extend their life cycle.

Fan delay

